System Reset
Monolithic IC PST600

Outline

This IC operates in a variety of CPU systems and other logic systems by detecting power supply voltage, so that the system can be reset accurately when power is turned on or when power is momentarily cut. PST572 and others perform the same function as does this series, but this IC is a low reset type system resetting IC which follows load current so that circuit current flow increases for ON, and has low current consumption for both ON and OFF.

Features

1. Follows load current so that circuit current flow increases for ON, and has low current consumption for both ON and OFF. No load : I_{CCL}=7μA typ.; I_{CCH}=5μA typ.
2. Low operating limit voltage 0.65V typ.
3. Hysteresis voltage provided in detection voltage 50mV typ.
4. The following 10 ranks of detection voltages are available.

PST600	C : 4.5V typ.	H : 3.1V typ.
	D : 4.2V typ.	I : 2.9V typ.
	E : 3.9V typ.	J : 2.7V typ.
	F : 3.6V typ.	K : 2.5V typ.
	G : 3.3V typ.	L : 2.3V typ.

Package

MMP-3A (PST600□M)
TO-92A (PST600□)
*□contains detection voltage rank.

Applications

1. Microcomputers, CPU, MPU reset circuits
2. Logic circuit reset circuits
3. Battery voltage check circuits
4. Back-up power supply switching circuits
5. Level detection circuits

Equivalent Circuit



Pin Assignment



TO-92A

1	Vcc
2	GND
3	Vout



MMP-3A

1	Vcc
2	GND
3	Vout

Absolute Maximum Ratings (Ta=25℃)

Item	Symbol	Ratings	Units
Storage temperature	Tstg	−40~+125	℃
Operating temperature	Topr	−20~+75	℃
Power supply voltage	Vcc max.	−0.3~10	V
Allowable loss	Pd	200 (MMP-3A) 300 (TO-92A)	mW

Electrical Characteristics (Ta=25℃) (unless otherwise indicated resistance unit is Ω)

Item	Symbol	Measurement circuit	Measurement conditions		Min.	Typ.	Max.	Units
Detection voltage	Vs	1	RL=470 VOL ≦ 0.4V Vcc=H→L	PST600C	4.3	4.5	4.7	V
				PST600D	4.0	4.2	4.4	
				PST600E	3.7	3.9	4.1	
				PST600F	3.4	3.6	3.8	
				PST600G	3.1	3.3	3.5	
				PST600H	2.9	3.1	3.3	
				PST600I	2.75	2.90	3.05	
				PST600J	2.55	2.70	2.85	
				PST600K	2.35	2.50	2.65	
				PST600L	2.15	2.30	2.45	
Hysteresis voltage	⊿Vs	1	RL=470, Vcc=L→H→L		30	50	100	mV
Detection voltage temperature coefficient	Vs/⊿T	1	RL=470, Ta=−20℃~+75℃			±0.01		%/℃
Low level output voltage	VOL	1	Vcc=Vs min. −0.05V, RL=470			0.3	0.4	V
Output leak current	IOH	1	Vcc=10V				±0.1	μA
Circuit current for ON	ICCL	1	Vcc=Vs min. −0.05V	IOL=0mA		7	14	μA
				IOL=8mA		50	130	
Circuit current for OFF	ICCH	1	Vcc=Vs typ./0.85V, RL=∞			5	10	μA
H transmission delay time	tPLH	2	RL=4.7k, CL=100pF ✶1		20	40	80	μS
L transmission delay time	tPHL	2	RL=4.7k, CL=100pF ✶1		10	20	40	μS
Operating limit voltage	VopL	1	RL=4.7k, VoL ≦ 0.4V			0.65	0.85	V
Output current 1 for ON	IOL 1	1	Vcc=Vs min. −0.05V, RL=0		8			mA
Output current 2 for ON	IOL 2	1	Ta=−20℃~+75℃, RL=0 ✶2		6			mA

✶1 tPLH : Vcc= (Vs typ. −0.4V) → (Vs typ.+0.4V), tPLH : Vcc= (Vs typ.+0.4V) → (Vs typ.−0.4V)

✶2 Vcc=Vs min. −0.15V

Measurement Circuit

[1]



[2]



* The input model is an example of PST600C (MMP-3P).

Characteristics (PST600C is used as the representative model for characteristics examples.)

Vcc vs. Vout



VoL vs. Ta



⊿Vs vs. Ta



Vs vs. Ta



IccL vs. IoL



IccH vs. Ta



IoL vs. Ta



VoL vs. IoL



IccL (IoL=0mA) vs. Ta



Application Circuits

1. Normal hard reset



Delay Time (tPLH)

$$\fallingdotseq C_L \times R_L \times \left[\ln \frac{V_{CC}}{V_{CC} - (V_{S\,CPU} + 0.2)} \right] + 0.040\ (mS)$$

C_L : µF $V_{S\,CPU}$: CPU, MPU reset threshold voltage

R_L : kΩ

Voltage : V

Note : When V_{CC} line impedance is high, connect a capacitor between IC Pins 1 and 2.

2. Manual Reset



Note : Prevent Manual SW chattering by using R_L, C_L and Rm. Rm setting conditions are as follows : Rm ≦ 1/20 R_L

Note : When V_{CC} line impedance is high,connect a capacitor between IC Pins 1 and 2.

3. Battery Checker (LED ON for High voltage)



Note : When V_{CC} line impedance is high, connect a capacitor between IC Pins 1 and 2.

4. Battery Checker (LED ON for Low voltage)



Note : When V_{CC} line impedance is high, connect a capacitor between IC Pins 1 and 2.